



Parameter	Curve	Best Fit Formula
K_T for ANT-72 with 34 ft. RG-223/U cable	1	$.004927f^{1.350}$
K_T for ANT-72 with 45 in. RG-223/U cable	2	$.01441f^{1.120}$
K_a for ANT-72 alone	3	$.01654f^{1.091}$

Curves based on calibration by National Bureau of Standards, Boulder, Colorado. (NBS Test No.810955, 21 August 1984)

Figure 2-5. Antenna Factor and Cable Loss (ratio)